



SERVICE BULLETIN

Title: 19EB/EF/FA High Voltage Motor Terminals

Models Affected: 19EB/EF/FA

Number: C9113

Date:

Supersedes:

Date:

Purpose:

To provide the field with a revised high voltage motor terminal selection guide.

Procedure:

The attached addendum sheet will replace the selection guide (Table 1) in service bulletin C8803 on page 5.

File: Specified Parts

Prepared By: Todd Young

Approved By: Alan Johnson

This document and the material contained herein are the property of Carrier Corporation and may not be copied, reproduced, or released without written permission of Carrier Corporation.

TABLE - 1
HI VOLTAGE MOTOR TERMINAL SELECTION GUIDE

MOTOR CODE	MOTOR SIZE	19EF						19FA						19EB						MODEL								
		60			50			60			50			60			50			CYCLES (Hz)								
		2400	3000	3300	4160	6900	3000	3300	6300	2400	3000	3300	4160	6900	3000	3300	6300	2400	3000	3300	4160	6900	3000	3300	6300	VOLTAGE (V)		
CB	C2								X	X	X	X																
CD	C4																											
CL	C6																											
CN	C8																											
DB	D2								X		X	X		X	X		X		X	X		X	X					
DC	D3																											
DD	D4								X		X	X	+	X	X	+						+			+			
DE	D5																									+		
DF	D6	X		X	X		X	X		X	X	X	+	X	X	+						+				+		
DG	D7																									+		○
DH	D8								X		X	X	+	X	X	○						+				+		○
DJ	D9																									+		○
DK	D10								X		X	X	○	X	X	○						○				○		○
DL	D11																									○		○
DM	D12								X		X	X	○	X	X	○						○				○		○
DN	D13																									○		○
DP	D14																									○		○
DQ	D14.6																									○		○
EA	E1								•		•	•	○	•	•	○												
EB	E2								•		•	•	○	•	•	○												
EC	E3								•		•	•	○	•	•	○												
ED	E4								•		•	•	○	•	•	○												

LEGEND			
COMP'R SIZE	SYMBOL	TERMINAL ARRANGEMENT	KIT PART NUMBER
4	X	19EF-402-173	19EF-660-001
	+	19EF-402-163	19EF-660-003
5	○	19EF-502-163	19EF-660-004
	○	19EF-502-163	19EF-660-004
5	•	19EF-502-173	19EF-660-002